Eng

VIVAX
Made for you

VIVAX VOX

VIVAX   **Model : BS-110**

Ean code   3856005191925

VIVAX · BT BLUETOOTH · mp3

Speaker System
BS-110

2 x 5.1 CM SPEAKER · 10 W RMS AUDIO POWER

UP TO 5,5h PLAY AT MODERATE VOLUME · 3000mAh RECHARGEABLE

DESCRIPTION	
Bluetooth Speaker, USB player; MP3; AUX LINE in 3,5mm ; USB in; 10W RMS Audio output (2x5,1cm speaker, 80Hz-16kHz), Power supply: 3000mAh Rechargable Battery; Deep and Powerfull Bass, Charging by Micro USB connection, Up to 5,5 hours Music Play (in moderate volume) / Up to 2,5 hours on Max Volume Play; TWS Pairing function; Hands Free Incomming call function; Side LED light, Stripe for easy carrying, IPX5 Protection class	

SPECIFICATIONS	
PLL FM Radio	-
AM Radio	-
Auto Radio search & Store	-
Programme memories	-
CD	-
Remote controler	-
LCD Display	Side LED lights, LED Light arround Soft Buttons (On/Off, Battery status)
BBS (Bass boost sound)	Yes
Equalizer function	-
Clock	-
Auto ON/OFF	Yes
Amplifier	2.0Ch, 10W RMS
Frequency range	80Hz - 16kHz +/- 3dB S/N:>70dB, Distortion: <0,1% 1kHz,1W

MULTIMEDIA	
MP3/WMA/FLAC/WAV/AAC	Yes / - / - / - / -
Other	TWS (True Wireless Stereo)-connect two speakers as a pair for a stronger stereo and surrounding effect ; Hands Free Incomming call function, IPX5 Protection class

TERMINALS	
AUX-IN / AUX Out	Yes, 3,5mm / -
STEREO HEADPHONE in	-
USB	Yes / MP3 Play
FM Antenna	-
SD/MMC	-
Power On/Off switch	Soft Buttons
Wireless MIC / MIC1 / GUITAR	- / - / -

POWER / DIMENSIONS	
Audio Power	2 x 10W RMS (80Hz-16kHz)
Speakers	2x Wide range speakers 2x2" (2x5,1cm)
W x H x D unit dimension	242 x 92 x 92 mm
W x H x D box dimension	262 x 117 x 115 mm
Weight Gross/Net	1,00 / 0,80kg
Power	Lithium Battery 3000mAh, 7,4V
Charging	Yes, Type-C USB connection

ACCESSORIES	
Instruction manual	English, Croatian, Serbian, Macedonian, Albanian, Slovenian + local market languages
Remote controller	-
Accessories	Type-C USB-USB Charger cable, Audio AUX 3,5mm cable, User Manual

* Due to different formats and codec format version, it is possible that all specified formats will not be supported. The manufacturer is not responsible for a such problems and it is not considered a malfunction of the device.